



## MATERIAL FACT SHEET

### 247596 FR-D720S-014SC-EC

#### General Data

Product Hierarchy	IAK23701
	INVERTER
	FR-D720
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	A (Available from Stock)

e-shop: [https://mitsubishi-electric-eshop.mee.com/mee/FA\\_IA/EUR/en/p/000000000000247596](https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000247596)

#### FA-Inverter: Inverter

Series	FR-D700 SERIES
Type	FR-D700 COMPACT INVERTER
Minimum Rated Voltage (V)	200
Min. Permissible Voltage (V)	170
Maximum Rated Voltage (V)	240
Max. Permissible Voltage (V)	264
Current Type	AC
Phases	1
Rated Output Current ND (A)	1,4
Rated Motor Capacity ND (kW)	0,2
Frequency Range (Hz)	0,2-400
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (3)	V/F CONTROL
Motor Type	INDUCTION MOTOR
Brake Chopper ED (%)	30
Integrated EMC Filter	NO
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	BUILT-IN
Display Type	4 DIGITS LED
PLC Function	NO
Integrated Digital Inputs	5
Digital Outputs (Transistor)	1
Digital Outputs (Relay)	1
Integrated Analogue Inputs	2
Integrated Analogue Outputs	1
IO Type of Terminal Block	SPRING CLAMP
Expandable	NO
RS-485	1
USB	NO
Ethernet Port	NO
Built-In Network	MODBUS-RTU
Leakage Current (mA)	1
Power Loss ND (W)	20
Standby Power Consumption (W)	5,5-14
Protection Class	IP20

#### Product Dimensions & Weight

Width (mm)	68
Height (mm)	128
Depth (mm)	80,5
Weight (kg)	0,5

#### Logistic Dimensions & Gross Weight

Length (cm)	23,0
-------------	------

Width (cm)	18,0
Height (cm)	10,0
Gross Weight (kg)	0,820
Volume (cdm)	4,140

### Stock Data

Planned Delivery Time (Days)	296
------------------------------	-----

### Life Cycle

Sales Start	05.03.2012
Predecessor	214190 / FR-D720S-014-EC

### Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	China (CN)
Preference Status (Supplier Declaration)	Non EU

### Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

### Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

### Documentation & Media Data

Manual URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2f94&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2f94&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en</a>
Certificates URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en</a>
CAD URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-D720S-014SC-EC&amp;doc-lang=en</a>

### Product Packaging

Cardboard (g)	485,75
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	2,2
Wood (g)	0
Glass (g)	0
Others (g)	0

### Compatible products

Material	Description / Price List Text / Classification
<a href="#">70727</a>	FR-A5 CBL 1 Cable for connecting Inverter and Programming panel; 1m Class 100100405: FA-Inverter: Cable
<a href="#">70728</a>	FR-A5 CBL 2,5 Cable for connecting Inverter and Programming panel; 2,5m Class 100100405: FA-Inverter: Cable
<a href="#">70729</a>	FR-A5 CBL 5 Cable for connecting Inverter and Programming panel; 5m Class 100100405: FA-Inverter: Cable
<a href="#">88426</a>	SC-FR-PC CONNECTION CABLE PC>INVERTER Programming Cable RS 232>RS485/422; 5m Class 100100405: FA-Inverter: Cable
<a href="#">127962</a>	BU-UFS 22J Brake Unit 200V; Contin. Braking Current 22A; 10sec peak current 34A Class 100100407: FA-Inverter: Brake Option

Material	Description / Price List Text / Classification
<a href="#">129633</a>	RUFC22J Brake Resistor for BU-UFS22J; 1,2kW; 1x12 Ohm Class 100100407: FA-Inverter: Brake Option
<a href="#">130833</a>	FR-UDA01 DIN-Rail Adaptor for FR-D720S-0,2k-0,75k Class 100100403: FA-Inverter: External Option
<a href="#">134968</a>	FR-BAL-S-B-0,2K Input Reactor; 1 ph.; 230 V; for 0,2 K Class 100100406: FA-Inverter: Choke
<a href="#">157514</a>	FR-DU07 Parameter Unit for inverter type FR-A700-NA Class 100100403: FA-Inverter: External Option
<a href="#">157515</a>	FR-ADP Adaptor Module for Operator Panel FR-DU07 Class 100100403: FA-Inverter: External Option
<a href="#">166134</a>	FR-PU07 Programming panel with LCD-Display for all units of FR-700 series Class 100100403: FA-Inverter: External Option
<a href="#">209052</a>	FR-PU07BB-L Programming Panel with Copy Function; batterypowered; all FR-700 units; w/o bat. Class 100100403: FA-Inverter: External Option
<a href="#">209735</a>	FFR-SI-4.5A-SS1 Sinusfilter for 200/230/400V Inverters;max. 4,5A;FT=4-16kHz;(W*H*D) 125*180*75mm Class 100100404: FA-Inverter: Filter
<a href="#">209755</a>	FFR-DT-10A-SS1 du/dt Filter for 400V Inverters; max. 10A; FT=2-16kHz; (W*H*D) 100*120*65mm Class 100100404: FA-Inverter: Filter
<a href="#">214795</a>	FR-PA07 Simple Parameter Unit for mounting on enclosure surface; for all FR-E700 Class 100100403: FA-Inverter: External Option
<a href="#">247646</a>	BH-D6 2P 6A TYPE C N MCB 2-poles, Rated current 6A, Operating characteristic C Class 100100801: FA-MCB: Miniature Circuit Breaker
<a href="#">254683</a>	NF32-SV 3P 6A Circuit breaker 3pole. In = 6A; Icu = Ics = 2,5kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
<a href="#">275503</a>	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
<a href="#">279143</a>	S-T10 AC200V 1A Magnetic contactor. 4kW; 1NO; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
<a href="#">279200</a>	S-T10 AC200V 1B Magnetic contactor. 4kW; 1NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
<a href="#">287431</a>	SD-T12 DC24V 1A1B Magnetic contactor. 5,5kW; 1NO + 1NC; Us = DC 24V Class 100101001: FA-MC: Magnetic Contactor
<a href="#">312348</a>	FFR-CS-050-14A-SF1 Radio Noise Filter for FR-E720S/E820S-0008-0030; C1: 20m, C2: 50m Class 100100404: FA-Inverter: Filter
<a href="#">312351</a>	FFR-CS-050-14A-SF1-LL Radio Noise Filter for FR-E720S/E820S-0008-0030; C1: 10m Class 100100404: FA-Inverter: Filter